

THE RADI ALGORITHM FOR SOLVING LARGE-SCALE ALGEBRAIC RICCATI EQUATIONS

Peter Benner ^{*} Zvonimir Bujanović [†] Patrick Kürschner [‡] Jens Saak [§]

Abstract

In recent years, several new approaches for solving the large-scale continuous-time algebraic Riccati equation have appeared in the literature. Amodei and Buchot suggest computing a low-dimensional invariant subspace of the associated Hamiltonian matrix. Simoncini and Lin also target the Hamiltonian matrix, but in a different way: they iterate on the Cayley-transformed matrix with various shifts. Wong and Balakrishnan directly generalize the Lyapunov ADI-method to the Riccati equation. In this paper we introduce another method, inspired by the Cholesky-factored variant of the Lyapunov ADI-method. The advantage of the new algorithm is in its immediate and efficient low-rank formulation, and a simpler implementation compared to the three algorithms mentioned above. We discuss the theoretical properties of the new method, as well as various shift selection strategies. Finally, we show that all of the seemingly different methods listed above in fact produce exactly the same iterates when used with the same parameters: they are algorithmically different descriptions of the same approximation sequence to the Riccati solution.

Keywords: matrix equations, algebraic Riccati equations, ADI iteration, low rank approximation

MSC: 15A24, 15A18, 65F15, 65F30, 93B52

1 Introduction

The continuous-time algebraic Riccati equation,

$$A^*X + XA + Q - XGX = 0, \quad (1)$$

where

$$Q = C^*C, \quad G = BB^*, \quad A \in \mathbb{R}^{n \times n}, \quad B \in \mathbb{R}^{n \times m}, \quad C \in \mathbb{R}^{p \times n},$$

appears frequently in various aspects of control theory, such as linear-quadratic optimal regulator problems, H_2 and H_∞ controller design and balancing-related model reduction. While the equation may have many solutions, for such applications one is interested in finding a so-called stabilizing solution: the unique positive semidefinite solution $X \in \mathbb{C}^{n \times n}$ such that the matrix $A - GX$ is stable (i.e. all of its eigenvalues belong to $\mathbb{C}_-$, the left half of the complex plane). This solution exists [21, 14] when the pair (A, G) is stabilizable (i.e. $\text{rank}[A - \lambda I, G] = n$, for all λ in the closed right half plane), and the pair (A, Q) is detectable (i.e. (A^*, Q^*) is stabilizable). These conditions are fulfilled generically, and we assume they hold throughout the paper.

^{*}Max Planck Institute for Dynamics of Complex Technical Systems, Magdeburg, Germany; e-mail: benner@mpi-magdeburg.mpg.de

[†]University of Zagreb, Department of Mathematics, Zagreb, Croatia; e-mail: zbujanov@math.hr

[‡]Max Planck Institute for Dynamics of Complex Technical Systems, Magdeburg, Germany; e-mail: kuerschner@mpi-magdeburg.mpg.de

[§]Max Planck Institute for Dynamics of Complex Technical Systems, Magdeburg, Germany; e-mail: saak@mpi-magdeburg.mpg.de

There are several algorithms for finding the numerical solution of (1). In the case when n is small enough, one can compute the eigen- or Schur decomposition of the associated Hamiltonian matrix

$$\mathcal{H} = \begin{bmatrix} A & G \\ Q & -A^* \end{bmatrix}, \quad (2)$$

and use an explicit formula for X , see [22, 14]. However, if the dimensions of the involved matrices prohibit the computation of a full eigenvalue- or Schur decomposition, specialized large-scale algorithms have to be constructed. In such scenarios, Riccati equations arising in applications have additional properties: A is sparse, and $p, m \ll n$, thus making the matrices Q and G of very-low rank compared to n . This in turn implies that the sought-after solution X will have a low numerical rank [2], and allows for construction of iterative methods that approximate X with a series of matrices stored in low-rank factored form. Most of these methods are engineered as generalized versions of algorithms for solving a large-scale Lyapunov equation [34, 12], which is a special case of (1) with $G = 0$.

The alternating directions implicit (ADI) method [38] is a well established iterative approach for computing solutions of Lyapunov and other linear matrix equations. There exists an array of ADI methods [8, 9, 23, 24, 29, 31, 38, 36, 37], covering both the ordinary and the generalized case. All of these methods have simple statements and efficient implementations [29]. One particular advantage of ADI methods is that they are very well suited for large-scale problems: the default formulation which works with full-size dense matrices can be transformed into a series of iteratively built approximations to the solution. Such approximations are represented in factored form, each factor having a very small rank compared to the dimensions of the input matrices. This makes ADI methods very suitable for large-scale applications.

Recently, Wong and Balakrishnan [40, 41] suggested a so-called quadratic ADI method (qADI) for solving the algebraic Riccati equation (1). Their method is a direct generalization of the Lyapunov ADI method, but only when considering the formulation working with full-size dense matrices. However, in the setting of the qADI algorithm, it appears impossible to apply a so-called Li–White trick [24], which is the usual method of obtaining a low-rank formulation of an ADI method. Wong and Balakrishnan do provide a low-rank variant of their algorithm, but this variant has an important drawback: in each step, all the low-rank factors have to be rebuilt from scratch. This has a large negative impact on the performance of the algorithm.

In this paper, we introduce a new low-rank variant of the ADI iteration for Riccati equations, RADI, which surpasses this drawback by building the low-rank factors incrementally. In each step, each factor is expanded by several columns and/or rows, while keeping the elements from the previous steps intact. By setting the quadratic coefficient B in (1) to zero, our method reduces to the low-rank formulation of the Lyapunov ADI method, see, e.g., [4, 8, 24, 29].

Apart from the qADI method, there are several other methods for solving the large-scale Riccati equation that have appeared in the literature recently. Amodei and Buchot [1] derive an approximation of the solution by computing small-dimensional invariant subspaces of the associated Hamiltonian matrix (2). Lin and Simoncini [25] also consider the Hamiltonian matrix, and construct the solution by running subspace iterations on its Cayley transforms. Massoudi, Opmeer, and Reis [26] have shown that the latter method can be obtained from the control theory point of view as well.

A surprising result is that all of the Riccati methods we mentioned so far are equivalent: the approximations they produce in each step are the same. This was already shown [2] for the original qADI algorithm of Wong and Balakrishnan, and the algorithm of Amodei and Buchot. In this paper we extend this equivalence to our new low-rank RADI method and the method of Lin and Simoncini. Further algorithms for computing low-rank approximate solutions of (1) are the extended [19] and rational Krylov subspace methods [35], the low-rank Newton-Kleinman ADI iteration [8, 10, 18, 30], and algorithms based on doubling [14, 15].

This paper is organized as follows: in Section 2, we recall the statements of the Lyapunov ADI method and the various Riccati methods, and introduce the new low-rank RADI algorithm. We also discuss several important implementation issues. In Section 3 we show the equivalence of all aforementioned methods. Finally, in Section 4 we discuss strategies for choosing shift parameters, and demonstrate different available options by running several numerical experiments.

We use the following notation in this paper: $\mathbb{C}_-$ and $\mathbb{C}_+$ are the open left and right half plane, respectively, while $\text{Re}(z)$, $\text{Im}(z)$, $\bar{z} = \text{Re}(z) - i\text{Im}(z)$, $|z|$ denote the real part, imaginary part, complex conjugate, and absolute value of a complex quantity z . For the matrix A , we use A^T , $A^* = \bar{A}^T$, A^{-1} for the transpose, the complex conjugate transpose, and the inverse, respectively. In most situations, expressions of the form $x = A^{-1}b$ are to be understood as solving the linear system $Ax = b$ of equations for b . The relations $A > (\geq) 0$, $A < (\leq) 0$ stand for the matrix A being positive or negative (semi)definite. Likewise, $A \geq (\leq) B$ refers to $A - B \geq (\leq) 0$. If not stated otherwise, $\|\cdot\|$ is the Euclidean vector or subordinate matrix norm, and $\kappa(\cdot)$ is the associated condition number.

2 A new low-rank factored iteration

We start this section by stating various methods for solving Lyapunov and Riccati equations, which will be used throughout the paper. First, consider the Lyapunov equation

$$A^* X^{\text{lya}} + X^{\text{lya}} A + Q = 0, \quad Q = C^* C, \quad A \in \mathbb{R}^{n \times n}, \quad C \in \mathbb{R}^{p \times n}. \quad (3)$$

Here we assume that n is much larger than p . When A is a stable matrix, the solution X^{lya} is positive semidefinite. The Lyapunov ADI algorithm [37] generates a sequence of approximations $(X_k^{\text{lya}})_k$ to X^{lya} defined by

$$\left. \begin{aligned} X_{k+1/2}^{\text{lya}}(A + \overline{\sigma_{k+1}}I) &= -Q - (A^* - \overline{\sigma_{k+1}}I)X_k^{\text{lya}}, \\ (A^* + \sigma_{k+1}I)X_{k+1}^{\text{lya}} &= -Q - X_{k+1/2}^{\text{lya}}(A - \sigma_{k+1}I). \end{aligned} \right\} \text{Lyapunov ADI} \quad (4)$$

We will assume that the initial iterate X_0^{lya} is the zero matrix, although it may be set arbitrarily. The complex numbers $\sigma_k \in \mathbb{C}_-$ are called shifts, and the performance of ADI algorithms depends strongly on the appropriate selection of these parameters [31]; this is further discussed in the context of the RADI method in Section 4. Since each iteration matrix X_k^{lya} is of order n , formulation (4) is unsuitable for large values of n , due to the amount of memory needed for storing $X_k^{\text{lya}} \in \mathbb{C}^{n \times n}$ and to the computational time needed for solving n linear systems in each half-step. The equivalent low-rank algorithm [3] generates the same sequence, but represents X_k^{lya} in factored form $X_k^{\text{lya}} = Z_k^{\text{lya}}(Z_k^{\text{lya}})^*$ with $Z_k^{\text{lya}} \in \mathbb{C}^{n \times pk}$:

$$\left. \begin{aligned} R_0^{\text{lya}} &= C^*, \\ V_k^{\text{lya}} &= \sqrt{-2 \text{Re}(\sigma_k)} \cdot (A^* + \sigma_k I)^{-1} R_{k-1}^{\text{lya}}, \\ R_k^{\text{lya}} &= R_{k-1}^{\text{lya}} + \sqrt{-2 \text{Re}(\sigma_k)} \cdot V_k^{\text{lya}}, \\ Z_k^{\text{lya}} &= \begin{bmatrix} Z_{k-1}^{\text{lya}} & V_k^{\text{lya}} \end{bmatrix}. \end{aligned} \right\} \text{low-rank Lyapunov ADI} \quad (5)$$

Initially, the matrix Z_0^{lya} is empty. This formulation is far more efficient for large values of n , since the right-hand side of the linear system in each step involves only the tall-and-skinny matrix $R_{k-1}^{\text{lya}} \in \mathbb{C}^{n \times p}$.

We now turn our attention to the Riccati equation (1). Once again we assume that $p, m \ll n$, and seek to approximate the stabilizing solution X . Wong and Balakrishnan [40, 41] suggest the following quadratic ADI iteration (abbreviated as qADI):

$$\left. \begin{aligned} X_{k+1/2}^{\text{adi}}(A + \overline{\sigma_{k+1}}I - GX_k^{\text{adi}}) &= -Q - (A^* - \overline{\sigma_{k+1}}I)X_k^{\text{adi}}, \\ (A^* + \sigma_{k+1}I - X_{k+1/2}^{\text{adi}}G)X_{k+1}^{\text{adi}} &= -Q - X_{k+1/2}^{\text{adi}}(A - \sigma_{k+1}I). \end{aligned} \right\} \text{quadratic ADI} \quad (6)$$

Again, the initial approximation is usually set to $X_0^{\text{adi}} = 0$. Note that by inserting $G = 0$ in the quadratic iteration we obtain the Lyapunov ADI algorithm (4). As mentioned in the introduction, we will develop a low-rank variant of this algorithm such that inserting $G = 0$ will reduce it precisely to (5). To prepare the terrain, we need to introduce two more methods for solving the Riccati equation.

In the small scale setting, the Riccati equation (1) is usually solved by computing the stable invariant subspace of the associated $2n \times 2n$ Hamiltonian matrix (2). To be more precise, let $1 \leq k \leq n$, and

$$\mathcal{H} \begin{bmatrix} P_k \\ Q_k \end{bmatrix} = \begin{bmatrix} A & G \\ Q & -A^* \end{bmatrix} \begin{bmatrix} P_k \\ Q_k \end{bmatrix} = \begin{bmatrix} P_k \\ Q_k \end{bmatrix} \Lambda_k, \quad (7)$$

where $P_k, Q_k \in \mathbb{C}^{n \times k}$ and the matrix $\Lambda_k \in \mathbb{C}^{k \times k}$ is stable. For $k = n$, the stabilizing solution of (1) is given by $X = -Q_k P_k^{-1}$. In the large scale setting, it is computationally too expensive to compute the entire n -dimensional stable invariant subspace of $\mathcal{H}$. Thus an alternative approach was suggested in [1]: for $k \ll n$, one can compute only a k -dimensional, stable, invariant subspace and use an approximation given by the formula

$$X_k^{\text{inv}} = -Q_k(Q_k^* P_k)^{-1} Q_k^*. \quad \} \text{ invariant subspace approach} \quad (8)$$

Clearly, $X_n^{\text{inv}} = X$. This approach was further studied and justified in [2], where it was shown that

$$X_k^{\text{inv}} = X_k^{\text{adi}}, \text{ for all } k,$$

if $p = 1$ and the shifts used for the qADI iteration coincide with the Hamiltonian eigenvalues of the matrix Λ_k . In fact, properties of the approximate solution X_k^{inv} given in [2] have lead us to the definition of the low-rank variant of the qADI iteration that is described in this paper.

The final method we consider also uses the Hamiltonian matrix $\mathcal{H}$. The Cayley transformed Hamiltonian subspace iteration introduced in [25] generates a sequence of approximations $(X_k^{\text{cay}})_k$ for the stabilizing solution of the Riccati equation defined by

$$\left\{ \begin{array}{l} \begin{bmatrix} M_k \\ N_k \\ X_k^{\text{cay}} \end{bmatrix} = (\mathcal{H} - \sigma_k I)^{-1} (\mathcal{H} + \overline{\sigma_k} I) \begin{bmatrix} I \\ -X_{k-1}^{\text{cay}} \end{bmatrix}, \\ X_k^{\text{cay}} = -N_k M_k^{-1}, \end{array} \right\} \text{ Cayley subspace iteration} \quad (9)$$

Here X_0^{cay} is some initial approximation and $\sigma_k \in \mathbb{C}_-$ are any chosen shifts (Here we have adapted the notation to fit the one of this paper). In Section 3 we will show that this method is also equivalent to the qADI and the new low-rank RADI iterations.

2.1 Derivation of the algorithm

The common way of converting ADI iterations into their low-rank variants is to perform a procedure similar to the one originally done by Li and White [24] for the Lyapunov ADI method. A crucial assumption for this procedure to succeed is that the matrices participating in the linear systems in each of the half-steps mutually commute for all k . For the Lyapunov ADI method this obviously holds true for the matrices $A^* + \sigma_{k+1} I$. However, in the case of the quadratic ADI iteration (6), the matrices $A^* + \sigma_{k+1} I - X_k^{\text{adi}} G$ do not commute in general, for all k , and neither do $A^* + \sigma_{k+1} I - X_{k+1/2}^{\text{adi}} G$.

Thus we take a different approach in constructing the low-rank version. A common way to measure the quality of the matrix $\Xi \in \mathbb{C}^{n \times n}$ as an approximation to the Riccati solution is to compute the norm of its residual matrix

$$\mathcal{R}(\Xi) = A^* \Xi + \Xi A + Q - \Xi G \Xi.$$

The idea for our method is to repetitively update the approximation Ξ by forming a so-called residual equation, until its solution converges to zero. The background is given in the following simple result.

Theorem 1. *Let $\Xi \in \mathbb{C}^{n \times n}$ be an approximation to a solution of (1).*

(a) *Let $X = \Xi + \tilde{X}$ be an exact solution of (1). Then $\tilde{X}$ is a solution to the residual equation*

$$\tilde{A}^* \tilde{X} + \tilde{X} \tilde{A} + \tilde{Q} - \tilde{X} G \tilde{X} = 0, \quad (10)$$

where $\tilde{A} = A - G \Xi$ and $\tilde{Q} = \mathcal{R}(\Xi)$.

- (b) Conversely, if $\tilde{X}$ is a solution to (10), then $X = \Xi + \tilde{X}$ is a solution to the original Riccati equation (1). Moreover, if $\Xi \geq 0$ and $\tilde{X}$ is a stabilizing solution to (10), then $X = \Xi + \tilde{X}$ is the stabilizing solution to (1).
- (c) If $\Xi \geq 0$ and $\mathcal{R}(\Xi) \geq 0$, then the residual equation (10) has a unique stabilizing solution.
- (d) If $\Xi \geq 0$ and $\mathcal{R}(\Xi) \geq 0$, then $\Xi \leq X$, where X is the stabilizing solution of (1).

Proof.

- (a) This is a straightforward computation which follows by inserting $\tilde{X} = X - \Xi$ and the formula for the residual of Ξ into (10), see also [13, 27].
- (b) The first part follows as in (a). If $\Xi \geq 0$ and $\tilde{X}$ is a stabilizing solution to (10), then $X = \Xi + \tilde{X} \geq 0$ and $A - GX = \tilde{A} - G\tilde{X}$ is stable, which makes X the stabilizing solution to (1).
- (c) Assume that the pair $(\tilde{A}, G)$ is not stabilizable. Then there exists $\lambda \in \mathbb{C}_+$ such that $\text{rank}[A - G\Xi - \lambda I, G] < n$, i.e. there is a non-zero $y \in \mathbb{C}^n$ such that $y^*[A - G\Xi - \lambda I, G] = 0$. But then $y^*G = 0$ and $y^*(A - \lambda I) = 0$, implying that (A, G) is not stabilizable, which is a contradiction. Therefore, $(\tilde{A}, G)$ is stabilizable, and since we have $G \geq 0$, $\tilde{Q} = \mathcal{R}(\Xi) \geq 0$, the residual equation (10) has a unique positive semidefinite solution $\tilde{X}$ such that all the eigenvalues of $\tilde{A} - G\tilde{X}$ lie in the closed complex left half-plane, see e.g. [14, Theorem 2.21]. However, then $X = \Xi + \tilde{X} \geq 0$ is a solution to (1) such that the eigenvalues of $A - GX$ are in the closed complex left half-plane. Such a solution to (1) must be stable since (A, Q) is detectable. Thus $\tilde{X}$ is also the unique stabilizing solution of the residual equation.
- (d) The claim follows directly from (b) and (c).

□

Our algorithm will have the following form:

1. Let $\Xi = 0$.
2. Form the residual equation (10) for the approximation Ξ .
3. Compute an approximation $\tilde{X}_1 \approx \tilde{X}$, where $\tilde{X}$ is the stabilizing solution of (10).
4. Accumulate $\Xi \leftarrow \Xi + \tilde{X}_1$, and go to Step 2.

To complete the derivation, we need to specify Step 3 in a way that $\tilde{X}_1 \geq 0$ and $\mathcal{R}(\Xi + \tilde{X}_1) \geq 0$. With these two conditions imposed, Theorem 1 ensures that the residual equation in Step 2 always has a unique stabilizing solution and that the approximation Ξ is kept positive semidefinite and monotonically increasing towards the stabilizing solution of (1). The matrix $\tilde{X}_1$ fulfilling these conditions can be obtained by computing a 1-dimensional invariant subspace for the Hamiltonian matrix associated with the residual equation, and plugging it into formula (8).

More precisely, assume that $\mathcal{R}(\Xi) = \tilde{C}^* \tilde{C} \geq 0$, $G = BB^*$, and that $r, q \in \mathbb{C}^n$ satisfy

$$\begin{bmatrix} \tilde{A} & BB^* \\ \tilde{C}^* \tilde{C} & -\tilde{A}^* \end{bmatrix} \begin{bmatrix} r \\ q \end{bmatrix} = \lambda \begin{bmatrix} r \\ q \end{bmatrix},$$

where $\lambda \in \mathbb{C}_-$ is such that $-\lambda$ is not an eigenvalue of $\tilde{A}$. Equivalently,

$$\begin{aligned} \tilde{A}r + BB^*q &= \lambda r, \\ \tilde{C}^* \tilde{C}r - \tilde{A}^*q &= \lambda q. \end{aligned}$$

From the second equation we get $q = (\tilde{A}^* + \lambda I)^{-1} \tilde{C}^* (\tilde{C}r)$. Let

$$\tilde{V}_1 = \sqrt{-2 \text{Re}(\lambda)} (\tilde{A}^* + \lambda I)^{-1} \tilde{C}^*.$$

Multiply the first equation by q^* from the left, and the transpose of the second by r from the right; then add the terms to obtain

$$q^*r = \frac{1}{2\operatorname{Re}(\lambda)}(q^*BB^*q + r^*\tilde{C}^*\tilde{C}r) = \frac{1}{2\operatorname{Re}(\lambda)}(\tilde{C}r)^* \left(I - \frac{1}{2\operatorname{Re}(\lambda)}(\tilde{V}_1^*B)(\tilde{V}_1^*B)^* \right) (\tilde{C}r).$$

Expression (8) has the form $\tilde{X}_1 = -q(q^*r)^{-1}q^*$. When $p = 1$ and $\tilde{C}r \neq 0$, the terms containing $\tilde{C}r$ cancel out, and we get

$$\left. \begin{aligned} \tilde{V}_1 &= \sqrt{-2\operatorname{Re}(\lambda)} \cdot (\tilde{A}^* + \lambda I)^{-1} \tilde{C}^*, \\ \tilde{Y}_1 &= I - \frac{1}{2\operatorname{Re}(\lambda)}(\tilde{V}_1^*B)(\tilde{V}_1^*B)^*, \\ \tilde{X}_1 &= \tilde{V}_1 \tilde{Y}_1^{-1} \tilde{V}_1^*. \end{aligned} \right\} \quad (11)$$

The expression above is well-defined even when λ is not an eigenvalue of the Hamiltonian matrix, and for $p > 1$ as well. The following proposition shows that the desired properties of the updated matrix $\Xi + \tilde{X}_1$ hold for any λ in the left half-plane which is not an eigenvalue of $-\tilde{A}$, and for all p .

Proposition 1. *Let $\Xi \geq 0$ be such that $\mathcal{R}(\Xi) = \tilde{C}^*\tilde{C} \geq 0$, and let $\lambda \in \mathbb{C}_-$ not be an eigenvalue of $-\tilde{A}$. The following holds true for the update matrix $\tilde{X}_1$ as defined in (11):*

- (a) $\tilde{X}_1 \geq 0$, i.e. $\Xi + \tilde{X}_1 \geq 0$.
- (b) $\mathcal{R}(\Xi + \tilde{X}_1) = \hat{C}^*\hat{C} \geq 0$, where $\hat{C}^* = \tilde{C}^* + \sqrt{-2\operatorname{Re}(\lambda)} \cdot \tilde{V}_1 \tilde{Y}_1^{-1}$.

Proof.

- (a) Positive definiteness of $\tilde{Y}_1$ (and then the semi-definiteness of $\tilde{X}_1$ as well) follows directly from $\operatorname{Re}(\lambda) < 0$.
- (b) Note that $\tilde{A}^*\tilde{V}_1 = \sqrt{-2\operatorname{Re}(\lambda)} \cdot \tilde{C}^* - \lambda\tilde{V}_1$, and $(\tilde{V}_1^*B)(\tilde{V}_1^*B)^* = 2\operatorname{Re}(\lambda)I - 2\operatorname{Re}(\lambda)\tilde{Y}_1$. We use these expressions to obtain:

$$\begin{aligned} \mathcal{R}(\Xi + \tilde{X}_1) &= \tilde{A}^*\tilde{X}_1 + \tilde{X}_1\tilde{A} + \mathcal{R}(\Xi) - \tilde{X}_1BB^*\tilde{X}_1 \\ &= (\tilde{A}^*\tilde{V}_1)\tilde{Y}_1^{-1}\tilde{V}_1^* + \tilde{V}_1\tilde{Y}_1^{-1}(\tilde{A}^*\tilde{V}_1)^* + \tilde{C}^*\tilde{C} - \tilde{V}_1\tilde{Y}_1^{-1}(\tilde{V}_1^*B)(\tilde{V}_1^*B)^*\tilde{Y}_1^{-1}\tilde{V}_1^* \\ &= \sqrt{-2\operatorname{Re}(\lambda)} \cdot \tilde{C}^*\tilde{Y}_1^{-1}\tilde{V}_1^* + \sqrt{-2\operatorname{Re}(\lambda)} \cdot \tilde{V}_1\tilde{Y}_1^{-1}\tilde{C} + \tilde{C}^*\tilde{C} \\ &\quad - 2\operatorname{Re}(\lambda) \tilde{V}_1\tilde{Y}_1^{-1}\tilde{Y}_1^{-1}\tilde{V}_1^* \\ &= (\tilde{C}^* + \sqrt{-2\operatorname{Re}(\lambda)} \cdot \tilde{V}_1\tilde{Y}_1^{-1}) \cdot (\tilde{C}^* + \sqrt{-2\operatorname{Re}(\lambda)} \cdot \tilde{V}_1\tilde{Y}_1^{-1})^*. \end{aligned}$$

□

We are now ready to state the new RADI algorithm. Starting with the initial approximation $X_0 = 0$, i.e. with $\mathcal{R}(X_0) = C^*C$, in each iteration we form the approximation (11) for the solution of the residual equation, and update the factors of $X_k = Z_k Y_k^{-1} Z_k^*$. Proposition 1 provides a very efficient update formula for the residual of X_k , whose factors we suggestively rename in the iteration below, so that $\mathcal{R}(X_k) = R_k R_k^*$.

$$\left. \begin{aligned} R_0 &= C^*, \\ V_k &= \sqrt{-2\operatorname{Re}(\sigma_k)} \cdot (A^* - X_{k-1}BB^* + \sigma_k I)^{-1} R_{k-1}, \\ \tilde{Y}_k &= I - \frac{1}{2\operatorname{Re}(\sigma_k)}(V_k^*B)(V_k^*B)^*, \quad Y_k = \begin{bmatrix} Y_{k-1} & \\ & \tilde{Y}_k \end{bmatrix}, \\ R_k &= R_{k-1} + \sqrt{-2\operatorname{Re}(\sigma_k)} \cdot V_k \tilde{Y}_k^{-1}, \\ Z_k &= \begin{bmatrix} Z_{k-1} & V_k \end{bmatrix}. \end{aligned} \right\} \text{RADI iteration} \quad (12)$$

The parameters $\sigma_k \in \mathbb{C}_-$ can be chosen at will. Note that any positive semi-definite X_0 can be used as an initial approximation, as long as its residual is positive semi-definite as well, and its low-rank Cholesky factorization can be computed. From the derivation of the RADI algorithm we have that

$$X_k = \sum_{i=1}^k V_i \tilde{Y}_i^{-1} V_i^*;$$

in formulation (12) of the method we have collected $V_1, \dots, V_k$ into the matrix Z_k , and $\tilde{Y}_1, \dots, \tilde{Y}_k$ into the block-diagonal matrix Y_k .

When $p = 1$ and all the shifts are chosen as eigenvalues of the Hamiltonian matrix associated with the initial Riccati equation (1), the update described in Proposition 1 reduces to [2, Theorem 5]. Thus in that case, the RADI algorithm reduces to the invariant subspace approach (8).

Furthermore, iteration (12) clearly reduces to the low-rank Lyapunov ADI method (5) when $B = 0$; in that case $Y_k = I$. The relation to the original qADI iteration (6) is not clear unless $p = 1$ and the shifts are chosen as eigenvalues of $\mathcal{H}$, in which case both of these methods coincide with the invariant subspace approach. We discuss this further in Section 3; now we turn our attention on how to implement the low-rank RADI algorithm (12) efficiently.

2.2 Implementation aspects of the RADI algorithm

There are several issues with the iteration (12) stated as is that should be addressed when designing an efficient computational routine: how to decide when the iterates X_k have converged, how to solve linear systems with matrices $A^* - X_{k-1}G + \sigma_k I$, and how to minimize the usage of complex arithmetic.

Computing the residual and the stopping criterion. Tracking the progress of the algorithm and deciding when the iterates have converged is very simple thanks to the connection between the iteration matrices $R_k \in \mathbb{C}^{n \times p}$ and the residuals $\mathcal{R}(X_k) = R_k R_k^*$. Computing the norm of $\mathcal{R}(X_k)$ is done in the following way:

$$\|\mathcal{R}(X_k)\| = \|R_k R_k^*\| = \|R_k^* R_k\|.$$

The reordering of the factors in the last step is valid for both the 2-norm and the Frobenius norm. By applying this trick, one only has to compute the norm of a $p \times p$ matrix instead of the original $n \times n$ matrix. The RADI iteration is stopped once the residual norm has decreased sufficiently relative to the initial residual norm $\|CC^*\|$ of the approximation $X_0 = 0$. Similar tricks have been used for the low-rank Lyapunov ADI method [39, 4] as well.

Solving linear systems in RADI. During the iteration, one has to evaluate the expression $(A^* - X_{k-1}G + \sigma_k I)^{-1} R_{k-1}$. Here the matrix A is assumed to be sparse, while $X_{k-1}G = (X_{k-1}B)B^*$ is low-rank. There are different options on how to solve this linear system; if one wants to use a direct sparse solver, the initial expression can be adapted by using the Sherman–Morrison–Woodbury (SMW) formula [17]. We introduce the matrix $K_k := X_k B$ and update it during the RADI iteration: $K_k = K_{k-1} + (V_k \tilde{Y}_k^{-1})(V_k^* B)$. Note that $V_k \tilde{Y}_k^{-1}$ also appears in the update of the residual factor, and that $V_k^* B$ appears in the computation of $\tilde{Y}_k$, so both have to be computed only once. The initial expression is rewritten as

$$\begin{aligned} & (A^* - K_{k-1}B^* + \sigma_k I)^{-1} R_{k-1} \\ &= (A^* + \sigma_k I)^{-1} R_{k-1} + \\ & \quad (A^* + \sigma_k I)^{-1} K_{k-1} (I - B^* (A^* + \sigma_k I)^{-1} K_{k-1})^{-1} B^* (A^* + \sigma_k I)^{-1} R_{k-1}. \end{aligned}$$

Thus in each RADI step one needs two linear solves with the same matrix $A^* + \sigma_k I$. A very similar technique is used in the low-rank Newton ADI solver for the Riccati equation [10, 8, 30, 18].

Minimizing the use of complex arithmetic. The RADI algorithm, implementing the two techniques described above is listed in Algorithm 1. To increase its efficiency, we will minimize the use of complex arithmetic. We do so by taking shift $\sigma_{k+1} = \overline{\sigma_k}$ immediately after the shift $\sigma_k \in \mathbb{C} \setminus \mathbb{R}$ has been used, and by merging these two consecutive RADI steps into a single one. This entire procedure will have only one operation involving complex matrices: a linear solve with the matrix $A^* - X_{k-1}G + \sigma_k I$ to compute V_k . There are two key observations to be made here. First, by modifying the iteration slightly, one can ensure that the matrices K_{k+1} , R_{k+1} , and Y_{k+1} are real and can be computed by using real arithmetic only, as shown in the upcoming technical proposition. Second, there is no need to compute V_{k+1} at all to proceed with the iteration: the next matrix V_{k+2} will once again be computed by using the residual R_{k+1} , the same way as in Algorithm 1.

ALGORITHM 1: The RADI iteration using complex arithmetic.

Input: matrices $A \in \mathbb{R}^{n \times n}$, $B \in \mathbb{R}^{n \times m}$, $C \in \mathbb{R}^{p \times n}$.

Output: approximation $X \approx ZY^{-1}Z^*$ for the solution of $A^*X + XA + C^*C - XBB^*X = 0$.

```

1  $R = C^*$ ;  $K = 0$ ;  $Y = []$ ;
2 while  $\|R^*R\| \geq \text{tol} \cdot \|CC^*\|$  do
3   Obtain the next shift  $\sigma$ ;
4   if first pass through the loop then
5      $Z = V = \sqrt{-2 \operatorname{Re}(\sigma)} \cdot (A^* + \sigma I)^{-1}R$ ;
6   else
7      $V = \sqrt{-2 \operatorname{Re}(\sigma)} \cdot (A^* - KB^* + \sigma I)^{-1}R$ ; // Use SMW if necessary
8      $Z = [Z \ V]$ ;
9   end
10   $\tilde{Y} = I - \frac{1}{2 \operatorname{Re}(\sigma)} \cdot (V^*B)(V^*B)^*$ ;  $Y = \begin{bmatrix} Y \\ \tilde{Y} \end{bmatrix}$ ;
11   $R = R + \sqrt{-2 \operatorname{Re}(\sigma)} \cdot (V\tilde{Y}^{-1})$ ;
12   $K = K + (V\tilde{Y}^{-1}) \cdot (V^*B)$ ;
13 end

```

We begin with a simple lemma that provides different representations of the residual factor.

Lemma 1. *Let*

$$R_k^{(1)} = \frac{1}{\sqrt{-2 \operatorname{Re}(\sigma_k)}} \cdot (A^* - X_k G - \overline{\sigma_k} I) V_k,$$

$$R_k^{(2)} = \frac{1}{\sqrt{-2 \operatorname{Re}(\sigma_{k+1})}} \cdot (A^* - X_k G + \sigma_{k+1} I) V_{k+1}.$$

Then $R_k^{(1)} = R_k^{(2)} = R_k$.

Proof. From the definition of the RADI iteration (12) it is obvious that $R_k^{(2)} = R_k$. Using $X_k = X_{k-1} + V_k \tilde{Y}_k^{-1} V_k^*$, and $V_k^* G V_k = 2 \operatorname{Re}(\sigma_k) I - 2 \operatorname{Re}(\sigma_k) \tilde{Y}_k$, we have

$$\begin{aligned}
R_k &= R_{k-1} + \sqrt{-2 \operatorname{Re}(\sigma_k)} V_k \tilde{Y}_k^{-1} \\
&= \frac{1}{\sqrt{-2 \operatorname{Re}(\sigma_k)}} \cdot (A^* - X_{k-1} G + \sigma_k I) V_k + \sqrt{-2 \operatorname{Re}(\sigma_k)} V_k \tilde{Y}_k^{-1} \\
&= \frac{1}{\sqrt{-2 \operatorname{Re}(\sigma_k)}} \cdot (A^* - X_k G - \overline{\sigma_k} I) V_k + \frac{1}{\sqrt{-2 \operatorname{Re}(\sigma_k)}} V_k \tilde{Y}_k^{-1} V_k^* G V_k \\
&\quad - \sqrt{-2 \operatorname{Re}(\sigma_k)} V_k + \sqrt{-2 \operatorname{Re}(\sigma_k)} V_k \tilde{Y}_k^{-1} \\
&= R_k^{(1)}.
\end{aligned}$$

□

Proposition 2. *Let $X_{k-1} = Z_{k-1} Y_{k-1}^{-1} Z_{k-1}^* \in \mathbb{R}^{n \times n}$ denote the Riccati approximate solution computed after $k-1$ RADI steps. Assume that R_{k-1} , V_{k-1} , K_{k-1} are real and that $\sigma := \sigma_k = \overline{\sigma_{k+1}} \in \mathbb{C} \setminus \mathbb{R}$. Let:*

$$\begin{aligned}
V_r &= (\operatorname{Re}(V_k))^* B, \quad V_i = (\operatorname{Im}(V_k))^* B, \\
F_1 &= \begin{bmatrix} -\operatorname{Re}(\sigma) V_r - \operatorname{Im}(\sigma) V_i \\ \operatorname{Im}(\sigma) V_r - \operatorname{Re}(\sigma) V_i \end{bmatrix}, \quad F_2 = \begin{bmatrix} V_r \\ V_i \end{bmatrix}, \quad F_3 = \begin{bmatrix} \operatorname{Im}(\sigma) I_p \\ \operatorname{Re}(\sigma) I_p \end{bmatrix}.
\end{aligned}$$

Then $X_{k+1} = Z_{k+1}Y_{k+1}^{-1}Z_{k+1}^*$, where:

$$\begin{aligned} Z_{k+1} &= [Z_{k-1} \quad \text{Re}(V_k) \quad \text{Im}(V_k)], \\ Y_{k+1} &= \begin{bmatrix} Y_{k-1} & \\ & \hat{Y}_{k+1} \end{bmatrix}, \\ \hat{Y}_{k+1} &= \begin{bmatrix} I_p & \\ & 1/2I_p \end{bmatrix} - \frac{1}{4|\sigma|^2 \text{Re}(\sigma)} F_1 F_1^* - \frac{1}{4\text{Re}(\sigma)} F_2 F_2^* - \frac{1}{2|\sigma|^2} F_3 F_3^*. \end{aligned}$$

The residual factor R_{k+1} and the matrix K_{k+1} can be computed as

$$\begin{aligned} R_{k+1} &= R_{k-1} + \sqrt{-2\text{Re}(\sigma)} \left([\text{Re}(V_k) \quad \text{Im}(V_k)] \hat{Y}_{k+1}^{-1} \right) (:, 1 : p), \\ K_{k+1} &= K_{k-1} + [\text{Re}(V_k) \quad \text{Im}(V_k)] \hat{Y}_{k+1}^{-1} \begin{bmatrix} V_r \\ V_i \end{bmatrix}. \end{aligned}$$

Proof. The idea of the proof is similar to [5, Theorem 1]; however, there is a major complication involving the matrix Y , which in the Lyapunov case is simply equal to the identity. Due to the technical complexity of the proof, we only display key intermediate results. To simplify notation, we use indices 0, 1, 2 instead of $k-1$, k , $k+1$, respectively.

We start by taking the imaginary part of the defining relation for $R_0^{(2)} = R_0$ in Lemma 1:

$$0 = (A^* - X_0 G + \text{Re}(\sigma) I) \cdot \text{Im}(V_1) + \text{Im}(\sigma) \cdot \text{Re}(V_1);$$

thus

$$V_1 = \text{Re}(V_1) + i \text{Im}(V_1) = \frac{-1}{\text{Im}(\sigma)} \underbrace{(A^* - X_0 G + \bar{\sigma} I)}_{A_0} \text{Im}(V_1).$$

We use this and the Sherman–Morrison–Woodbury formula to compute V_2 :

$$\begin{aligned} V_2 &= \sqrt{-2\text{Re}(\sigma)} (A^* - X_1 G + \bar{\sigma} I)^{-1} R_1 \\ &= \sqrt{-2\text{Re}(\sigma)} (A^* - X_1 G + \bar{\sigma} I)^{-1} \cdot \frac{1}{\sqrt{-2\text{Re}(\sigma)}} \cdot (A^* - X_1 G - \bar{\sigma} I) V_1 \\ &= V_1 - 2\bar{\sigma} (A^* - X_1 G + \bar{\sigma} I)^{-1} V_1 \\ &= V_1 - 2\bar{\sigma} \left(A_0 - V_1 \tilde{Y}_1^{-1} (V_1^* G) \right)^{-1} V_1 \\ &= V_1 - 2\bar{\sigma} (A_0^{-1} V_1 + A_0^{-1} V_1 (\tilde{Y}_1 - (V_1^* G) A_0^{-1} V_1)^{-1} (V_1^* G) A_0^{-1} V_1) \\ &= V_1 + 2\bar{\sigma} \text{Im}(V_1) \underbrace{(\text{Im}(\sigma) \tilde{Y}_1 + (V_1^* B) V_i^*)^{-1}}_S \tilde{Y}_1. \end{aligned} \tag{13}$$

Next,

$$\begin{aligned} X_2 &= X_0 + [V_1 \ V_2] \begin{bmatrix} \tilde{Y}_1^{-1} \\ \tilde{Y}_2^{-1} \end{bmatrix} [V_1 \ V_2]^* \\ &= X_0 + [\text{Re}(V_1) \quad \text{Im}(V_1)] \underbrace{\begin{bmatrix} I & I \\ iI & iI + 2\bar{\sigma} S^{-1} \tilde{Y}_1 \end{bmatrix}}_T \begin{bmatrix} \tilde{Y}_1^{-1} \\ \tilde{Y}_2^{-1} \end{bmatrix} \left([\text{Re}(V_1) \quad \text{Im}(V_1)] \begin{bmatrix} I & I \\ iI & iI + 2\bar{\sigma} S^{-1} \tilde{Y}_1 \end{bmatrix} \right)^* \\ &= X_0 + [\text{Re}(V_1) \quad \text{Im}(V_1)] \underbrace{\left(T^{-*} \begin{bmatrix} \tilde{Y}_1 \\ \tilde{Y}_2 \end{bmatrix} T^{-1} \right)^{-1}}_{\tilde{Y}_2} [\text{Re}(V_1) \quad \text{Im}(V_1)]^*. \end{aligned}$$

We first compute T^{-1} by using the SMW formula once again:

$$\begin{aligned} T^{-1} &= \left(\begin{bmatrix} I & I \\ iI & iI \end{bmatrix} + \begin{bmatrix} I & \\ & S^{-1} \end{bmatrix} \begin{bmatrix} I & \\ & 2\bar{\sigma} \tilde{Y}_1 \end{bmatrix} \right)^{-1} \\ &= \begin{bmatrix} I + \frac{i}{2\bar{\sigma}} \tilde{Y}_1^{-1} S & \frac{-1}{2\bar{\sigma}} \tilde{Y}_1^{-1} S \\ \frac{-1}{2\bar{\sigma}} \tilde{Y}_1^{-1} S & \frac{1}{2\bar{\sigma}} \tilde{Y}_1^{-1} S \end{bmatrix}, \end{aligned}$$

and, applying the congruence transformation with T^{-1} to $\begin{bmatrix} \tilde{Y}_1 \\ \tilde{Y}_2 \end{bmatrix}$ yields

$$\hat{Y}_2 = \begin{bmatrix} \tilde{Y}_1 + \frac{i}{2\bar{\sigma}}S - \frac{i}{2\sigma}S^* + \frac{1}{4|\sigma|^2}S^*\tilde{Y}_1^{-1}S + \frac{1}{4|\sigma|^2}S^*\tilde{Y}_1^{-1}\tilde{Y}_2\tilde{Y}_1^{-1}S & \frac{-1}{2\bar{\sigma}}S + \frac{i}{4|\sigma|^2}S^*\tilde{Y}_1^{-1}S + \frac{i}{4|\sigma|^2}S^*\tilde{Y}_1^{-1}\tilde{Y}_2\tilde{Y}_1^{-1}S \\ \frac{-1}{2\sigma}S^* - \frac{i}{4|\sigma|^2}S^*\tilde{Y}_1^{-1}S - \frac{i}{4|\sigma|^2}S^*\tilde{Y}_1^{-1}\tilde{Y}_2\tilde{Y}_1^{-1}S & \frac{1}{4|\sigma|^2}S^*\tilde{Y}_1^{-1}S + \frac{1}{4|\sigma|^2}S^*\tilde{Y}_1^{-1}\tilde{Y}_2\tilde{Y}_1^{-1}S \end{bmatrix}.$$

By using (13), it is easy to show

$$\tilde{Y}_2 = -\tilde{Y}_1 - \frac{1}{2\operatorname{Re}(\sigma)} \left(-2\sigma \operatorname{Im}(\sigma) \tilde{Y}_1 S^{-*} \tilde{Y}_1 - 2\bar{\sigma} \operatorname{Im}(\sigma) \tilde{Y}_1 S^{-1} \tilde{Y}_1 + 4|\sigma|^2 \tilde{Y}_1 S^{-*} V_i V_i^* S^{-1} \tilde{Y}_1 \right).$$

Inserting this into the formula for $\hat{Y}_2$, all terms containing inverses of $\tilde{Y}_1$ and S cancel out. By rearranging the terms that do appear in the formula, we get the expression from the claim of the proposition.

Deriving the formulae for R_2 and K_2 is straightforward:

$$\begin{aligned} K_2 &= K_0 + \begin{bmatrix} V_1 & V_2 \end{bmatrix} \begin{bmatrix} \tilde{Y}_1^{-1} \\ \tilde{Y}_2^{-1} \end{bmatrix} \begin{bmatrix} V_1 & V_2 \end{bmatrix}^* B \\ &= K_0 + \left(\begin{bmatrix} \operatorname{Re}(V_1) & \operatorname{Im}(V_1) \end{bmatrix} \hat{Y}_2^{-1} \right) \left(\begin{bmatrix} \operatorname{Re}(V_1) & \operatorname{Im}(V_1) \end{bmatrix}^* B \right), \\ R_2 &= R_0 + \sqrt{-2\operatorname{Re}(\sigma)} \begin{bmatrix} V_1 & V_2 \end{bmatrix} \begin{bmatrix} \tilde{Y}_1^{-1} \\ \tilde{Y}_2^{-1} \end{bmatrix} \\ &= R_0 + \sqrt{-2\operatorname{Re}(\sigma)} \begin{bmatrix} \operatorname{Re}(V_1) & \operatorname{Im}(V_1) \end{bmatrix} \left(T \begin{bmatrix} \tilde{Y}_1^{-1} \\ \tilde{Y}_2^{-1} \end{bmatrix} \right) \\ &= R_0 + \sqrt{-2\operatorname{Re}(\sigma)} \begin{bmatrix} \operatorname{Re}(V_1) & \operatorname{Im}(V_1) \end{bmatrix} \hat{Y}_2^{-1}(:, 1:p), \end{aligned}$$

where the last line is due to the structure of the matrix T . Since the matrix $\hat{Y}_2$ is real, so are K_2 and R_2 . $\square$

Algorithm 2 shows the final implementation, taking into account Proposition 2.

RADI iteration for the generalized Riccati equation. The RADI algorithm can be easily adapted for solving the generalized Riccati equation

$$A^* X E + E^* X A + Q - E^* X G X E = 0. \quad (14)$$

For simplicity, we only display the variant that uses complex arithmetic. Inserting $\hat{X} = E^* X E$ into (14) leads to

$$(E^{-1}A)^* \hat{X} + \hat{X} (E^{-1}A) + Q - \hat{X} (E^{-1}B)(E^{-1}B)^* \hat{X} = 0. \quad (15)$$

The generalized RADI algorithm is derived by running ordinary RADI iterations for the Riccati equation (15). This leads to Algorithm 3.

3 Equivalences with other Riccati methods

In this section we prove that all Riccati solvers introduced in Section 2 in fact compute exactly the same iterations, which we will refer to as the Riccati ADI iterations in the remaining text. This result is collected in the following theorem.

Theorem 2. *If the initial approximation in all algorithms is zero, and the same shifts are used, then for all k ,*

$$X_k = X_k^{\text{adi}} = X_k^{\text{cay}}.$$

If $\operatorname{rank} C = 1$ and the shifts are equal to distinct eigenvalues of $\mathcal{H}$, then for all k ,

$$X_k = X_k^{\text{adi}} = X_k^{\text{cay}} = X_k^{\text{inv}}.$$

ALGORITHM 2: The RADI iteration, use of complex arithmetic is minimized.

Input: matrices $A \in \mathbb{R}^{n \times n}$, $B \in \mathbb{R}^{n \times m}$, $C \in \mathbb{R}^{p \times n}$.

Output: approximation $X \approx ZY^{-1}Z^*$ for the solution of

$A^*X + XA + C^*C - XBB^*X = 0$. The matrices Z and Y are real.

```

1  $R = C^*$ ;  $K = 0$ ;  $Y = []$ ;  $Z = []$ ;
2 while  $\|R^*R\| \geq \text{tol} \cdot \|CC^*\|$  do
3   Obtain the next shift  $\sigma$ ;

4   if first pass through the loop then
5      $V = \sqrt{-2\text{Re}(\sigma)} \cdot (A^* + \sigma I)^{-1}R$ ;
6   else
7      $V = \sqrt{-2\text{Re}(\sigma)} \cdot (A^* - KB^* + \sigma I)^{-1}R$ ; // Use SMW if necessary
8   end

9   if  $\sigma \in \mathbb{R}$  then
10     $Z = [Z \ V]$ ;
11     $\tilde{Y} = I - \frac{1}{2\text{Re}(\sigma)} \cdot (V^*B)(V^*B)^*$ ;  $Y = \begin{bmatrix} Y \\ \tilde{Y} \end{bmatrix}$ ;  $R = R + \sqrt{-2\text{Re}(\sigma)} \cdot (V\tilde{Y}^{-1})$ ;
12     $K = K + (V\tilde{Y}^{-1}) \cdot (V^*B)$ ;
13  else
14     $Z = [Z \ \text{Re}(V) \ \text{Im}(V)]$ ;
15     $V_r = (\text{Re}(V))^*B$ ;  $V_i = (\text{Im}(V))^*B$ ;
16     $F_1 = \begin{bmatrix} -\text{Re}(\sigma)V_r - \text{Im}(\sigma)V_i \\ \text{Im}(\sigma)V_r - \text{Re}(\sigma)V_i \end{bmatrix}$ ;  $F_2 = \begin{bmatrix} V_r \\ V_i \end{bmatrix}$ ;  $F_3 = \begin{bmatrix} \text{Im}(\sigma)I_p \\ \text{Re}(\sigma)I_p \end{bmatrix}$ ;
17     $\tilde{Y} = \begin{bmatrix} I_p & \\ & 1/2I_p \end{bmatrix} - \frac{1}{4|\sigma|^2\text{Re}(\sigma)}F_1F_1^* - \frac{1}{4\text{Re}(\sigma)}F_2F_2^* - \frac{1}{2|\sigma|^2}F_3F_3^*$ ;
18     $Y = \begin{bmatrix} Y \\ \tilde{Y} \end{bmatrix}$ ;
19     $R = R + \sqrt{-2\text{Re}(\sigma)} \left( [\text{Re}(V) \ \text{Im}(V)]\tilde{Y}^{-1} \right) (:, 1:p)$ ;
20     $K = K + [\text{Re}(V) \ \text{Im}(V)]\tilde{Y}^{-1} \begin{bmatrix} V_r \\ V_i \end{bmatrix}$ ;
21  end
22 end
```

ALGORITHM 3: The RADI iteration for the generalized Riccati equation.

Input: matrices $E, A \in \mathbb{R}^{n \times n}$, $B \in \mathbb{R}^{n \times m}$, $C \in \mathbb{R}^{p \times n}$.

Output: approximation $X \approx ZY^{-1}Z^*$ for the solution of
 $A^*XE + E^*XA + C^*C - E^*XBB^*XE = 0$.

```

1  $R = C^*$ ;  $K = 0$ ;  $Y = []$ ;
2 while  $\|R^*R\| \geq \text{tol} \cdot \|CC^*\|$  do
3   Obtain the next shift  $\sigma$ ;
4   if first pass through the loop then
5      $Z = V = \sqrt{-2 \operatorname{Re}(\sigma)} \cdot (A^* + \sigma E^*)^{-1}R$ ;
6   else
7      $V = \sqrt{-2 \operatorname{Re}(\sigma)} \cdot (A^* - KB^* + \sigma E^*)^{-1}R$ ; // Use SMW if necessary
8      $Z = [Z \ V]$ ;
9   end
10   $\tilde{Y} = I - \frac{1}{2 \operatorname{Re}(\sigma)} \cdot (V^*B)(V^*B)^*$ ;  $Y = [Y \ \tilde{Y}]$ ;
11   $R = R + \sqrt{-2 \operatorname{Re}(\sigma)} \cdot (E^*V\tilde{Y}^{-1})$ ;
12   $K = K + (E^*V\tilde{Y}^{-1}) \cdot (V^*B)$ ;
13 end

```

Proof. We first use induction to show that $X_k = X_k^{\text{adi}}$, for all k .

Assume that $X_{k-1} = X_{k-1}^{\text{adi}}$. We need to show that $X_k = X_{k-1} + V_k \tilde{Y}_k^{-1} V_k^*$ satisfies the defining equality (6) of the qADI iteration, i.e. that

$$(A^* + \sigma_k I - X_{k-1/2}^{\text{adi}} G)(X_{k-1} + V_k \tilde{Y}_k^{-1} V_k^*) = -Q - X_{k-1/2}^{\text{adi}}(A - \sigma_k I), \quad (16)$$

where

$$X_{k-1/2}^{\text{adi}}(A + \bar{\sigma}_k I - GX_{k-1}) = -Q - (A^* - \bar{\sigma}_k I)X_{k-1}. \quad (17)$$

First, note that (17) can be rewritten as

$$A^*X_{k-1} + X_{k-1/2}^{\text{adi}}A + Q - X_{k-1/2}^{\text{adi}}GX_{k-1} + \bar{\sigma}_k(X_{k-1/2}^{\text{adi}} - X_{k-1}) = 0.$$

Subtracting this from the expression for the Riccati residual,

$$A^*X_{k-1} + X_{k-1}A + Q - X_{k-1}GX_{k-1} = \mathcal{R}(X_{k-1}),$$

we obtain

$$X_{k-1/2}^{\text{adi}} - X_{k-1} = -\mathcal{R}(X_{k-1}) \cdot (A - GX_{k-1} + \bar{\sigma}_k I)^{-1}. \quad (18)$$

Equation (16) can be reorganized as

$$\begin{aligned} (A^* + \sigma_k I)(X_{k-1} + V_k \tilde{Y}_k^{-1} V_k^*) - X_{k-1/2}^{\text{adi}} G V_k \tilde{Y}_k^{-1} V_k^* \\ = -Q - X_{k-1/2}^{\text{adi}}(A + \bar{\sigma}_k I - GX_{k-1}) + 2 \operatorname{Re}(\sigma_k) X_{k-1/2}^{\text{adi}}. \end{aligned}$$

Replace the second term on the right-hand side with the right-hand side of (17). Thus it remains to prove

$$(A^* + \sigma_k I)(X_{k-1} + V_k \tilde{Y}_k^{-1} V_k^*) - X_{k-1/2}^{\text{adi}} G V_k \tilde{Y}_k^{-1} V_k^* = (A^* - \bar{\sigma}_k I)X_{k-1} + 2 \operatorname{Re}(\sigma_k) X_{k-1/2}^{\text{adi}},$$

or after some rearranging, and by using (18),

$$\begin{aligned} (A^* - X_{k-1}G + \sigma_k I)V_k \tilde{Y}_k^{-1} V_k^* \\ = (X_{k-1/2}^{\text{adi}} - X_{k-1}) \cdot (2 \operatorname{Re}(\sigma_k) I + G V_k \tilde{Y}_k^{-1} V_k^*) \\ = -\mathcal{R}(X_{k-1}) \cdot (A - GX_{k-1} + \bar{\sigma}_k I)^{-1} \cdot (2 \operatorname{Re}(\sigma_k) I + G V_k \tilde{Y}_k^{-1} V_k^*). \end{aligned} \quad (19)$$

Next we use the expression $\mathcal{R}(X_{k-1}) = R_{k-1}^{(2)}(R_{k-1}^{(2)})^*$ of Lemma 1. The right-hand side of (19) is thus equal to

$$\frac{1}{2\operatorname{Re}(\sigma_k)} \cdot (A^* - X_{k-1}G + \sigma_k I)V_k V_k^* \cdot (2\operatorname{Re}(\sigma_k)I + GV_k \tilde{Y}_k^{-1} V_k^*),$$

which turns out to be precisely the same as the left-hand side of (19) once we use the identity

$$V_k^* G V_k = 2\operatorname{Re}(\sigma_k)I - 2\operatorname{Re}(\sigma_k)\tilde{Y}_k.$$

This completes the proof of $X_k = X_k^{\text{adi}}$.

Next, we use induction once again to show $X_k^{\text{cay}} = X_k^{\text{adi}}$, for all k . For $k = 0$, the claim is trivial; assume that $X_{k-1}^{\text{cay}} = X_{k-1}^{\text{adi}}$ for some $k \geq 1$. To show that $X_k^{\text{cay}} = X_k^{\text{adi}}$, let us first multiply (9) by $\mathcal{H} - \sigma_k I$ from the left:

$$\begin{bmatrix} A - \sigma_k I & G \\ Q & -A^* - \sigma_k I \end{bmatrix} \begin{bmatrix} M_k \\ N_k \end{bmatrix} = \begin{bmatrix} A + \overline{\sigma_k} I & G \\ Q & -A^* + \overline{\sigma_k} I \end{bmatrix} \begin{bmatrix} I \\ -X_{k-1}^{\text{cay}} \end{bmatrix} =: \begin{bmatrix} M_{k-1/2} \\ N_{k-1/2} \end{bmatrix}, \quad (20)$$

and suggestively introduce $X_{k-1/2}^{\text{cay}} := -N_{k-1/2}M_{k-1/2}^{-1}$. We thus have

$$A + \overline{\sigma_k} I - G X_{k-1}^{\text{cay}} = M_{k-1/2}, \quad (21)$$

$$Q - (-A^* + \overline{\sigma_k} I) X_{k-1}^{\text{cay}} = N_{k-1/2}, \quad (22)$$

and

$$X_{k-1/2}^{\text{cay}}(A + \overline{\sigma_k} I - G X_{k-1}^{\text{cay}}) = -N_{k-1/2}M_{k-1/2}^{-1}M_{k-1/2} = -Q - (A^* - \overline{\sigma_k} I)X_{k-1}^{\text{cay}}.$$

This is the same relation as the one defining $X_{k-1/2}^{\text{adi}}$, and thus $X_{k-1/2}^{\text{cay}} = X_{k-1/2}^{\text{adi}}$. Next, equating the leftmost and the rightmost matrix in (20), it follows that

$$(A - \sigma_k I)M_k + G N_k = M_{k-1/2}, \quad (23)$$

$$Q M_k + (-A^* - \sigma_k I)N_k = N_{k-1/2}. \quad (24)$$

Multiply (24) from the right by M_k^{-1} to obtain

$$(A^* + \sigma_k I)X_k^{\text{cay}} = -Q + N_{k-1/2}M_k^{-1}, \quad (25)$$

and multiply (23) from the left by $X_{k-1/2}^{\text{cay}}$ and from the right by M_k^{-1} to get

$$-X_{k-1/2}^{\text{cay}} G X_k^{\text{cay}} = -X_{k-1/2}^{\text{cay}}(A - \sigma_k I) - N_{k-1/2}M_k^{-1}. \quad (26)$$

Adding (25) and (26) yields

$$(A^* + \sigma_k I - X_{k-1/2}^{\text{cay}} G)X_k^{\text{cay}} = -Q - X_{k-1/2}^{\text{cay}}(A - \sigma_k I),$$

which is the same as the defining equation for X_k^{adi} . Thus $X_k^{\text{cay}} = X_k^{\text{adi}}$, so both the Cayley subspace iteration and the qADI iteration generate the same sequences.

In the case of $\operatorname{rank} C = 1$ and shifts equal to the eigenvalues of $\mathcal{H}$, the equality $X_k^{\text{inv}} = X_k^{\text{adi}}$ is already shown in [2]. Equality among the iterates generated by the other methods is a special case of what we have proved above. $\square$

It is interesting to observe that [25, 26] also provide a low-rank variant of the Cayley subspace iteration algorithm: they give formulas for updating the factors of $X_k^{\text{cay}} = Z_k^{\text{cay}}(Y_k^{\text{cay}})^{-1}(Z_k^{\text{cay}})^*$, where $Z_k^{\text{cay}} \in \mathbb{C}^{n \times pk}$ and $Y_k^{\text{cay}} \in \mathbb{C}^{pk \times pk}$. The main difference in comparison to our RADI variant of the low-rank Riccati ADI iterations is that they use the matrix $(A^* + \sigma_k I)^{-1}$ instead of $(A^* - X_{k-1}G + \sigma_k I)^{-1}$ when computing Z_k^{cay} . This way, the need for using the Sherman–Morrison–Woodbury formula is

avoided. However, the consequence is a significantly more complicated update of the matrix Y_k^{cay} , which in turn loses its block-diagonal structure. Also, it is very difficult to derive a version of the algorithm that would use real arithmetic. Another disadvantage is the computation of the residual: along with Z_k^{cay} and Y_k^{cay} , one needs to maintain a QR-factorization of the matrix $[C^* \ A^* Z_k^{\text{cay}} \ Z_k^{\text{cay}}]$, which adds significant computational complexity to the algorithm. Both [25] and [26] notice that setting $B = 0$ reduces the Cayley subspace iteration algorithm to Lyapunov ADI method; they do not provide any connection to the qADI algorithm nor the Hamiltonian invariant subspace method.

Each of these different statements of the same Riccati ADI algorithm may contribute when studying theoretical properties of the iteration. For example, directly from our definition (12) of the RADI iteration it is obvious that

$$0 \leq X_1 \leq X_2 \leq \dots \leq X_k \leq \dots \leq X,$$

where the relation $\leq$ is defined by the Löwner partial order. Also, the fact that the residual matrix $\mathcal{R}(X_k)$ is low-rank and its explicit factorization follows naturally from our approach. On the other hand, approaching the iteration from the control theory point of view as in [26] is more suitable for proving that the so-called non-Blaschke condition for the shifts

$$\sum_{k=1}^{\infty} \frac{\operatorname{Re}(\sigma_k)}{1 + |\sigma_k|^2} = -\infty$$

is sufficient for achieving the convergence when A is stable, i.e.

$$\lim_{k \rightarrow \infty} X_k = X.$$

We conclude this section by noting a relation between the Riccati ADI iteration and the rational Krylov subspace method [35]. It is easy to see that the RADI iteration also uses the rational Krylov subspaces as the basis for approximation. Although this fact follows also from the low-rank formulation for X_k^{cay} as given in [25], we show it directly in the following proposition.

Proposition 3. *For a matrix M , (block-)vector v and a tuple $\vec{\sigma}_k = (\sigma_1, \dots, \sigma_k) \in \mathbb{C}_-^k$, let*

$$\mathcal{K}(M, v, \vec{\sigma}_k) = \operatorname{span}\{(M + \sigma_1 I)^{-1}v, (M + \sigma_2 I)^{-1}v, \dots, (M + \sigma_k I)^{-1}v\}$$

denote the rational Krylov subspace generated by M and the initial vector v . Then the columns of X_k belong to $\mathcal{K}(A^*, C^*, \vec{\sigma}_k)$.

Proof. Since $X_k = Z_k Y_k^{-1} Z_k^*$, it follows that the columns of X_k belong to $\operatorname{span}\{Z_k\}$. We show that these lie in $\mathcal{K}(A^*, C^*, \vec{\sigma}_k)$ by using induction. For $k = 1$,

$$V_1 = \sqrt{-2 \operatorname{Re}(\sigma_1)} \cdot (A^* + \sigma_1 I)^{-1} C^*,$$

so the claim is obvious. Suppose that $\operatorname{span}\{Z_{k-1}\}$ is a subspace of the rational Krylov subspace $\mathcal{K}(A^*, C^*, \vec{\sigma}_{k-1})$ generated by the shifts $\sigma_1, \dots, \sigma_{k-1}$. Since

$$V_k = \alpha_k V_{k-1} + \beta_k (A^* - X_{k-1} G + \sigma_k I)^{-1} V_{k-1}$$

for some complex numbers α_k and β_k , after using the Sherman–Morrison–Woodbury formula we have that

$$\begin{aligned} V_k &= \alpha_k V_{k-1} + \beta_k (A^* + \sigma_k I)^{-1} V_{k-1} \\ &\quad + \beta_k (A^* + \sigma_k I)^{-1} Z_{k-1} Y_{k-1}^{-1} Z_{k-1}^* (I - G A^{-*} X_{k-1})^{-1} G (A^* + \sigma_k I)^{-1} V_{k-1} \\ &\in \mathcal{K}(A^*, C^*, \vec{\sigma}_{k-1}) + (A^* + \sigma_k I)^{-1} \mathcal{K}(A^*, C^*, \vec{\sigma}_{k-1}) \\ &\subseteq \mathcal{K}(A^*, C^*, \vec{\sigma}_k). \end{aligned}$$

Here the element symbol is understood column-wise. □

From the proposition we conclude the following: if U_k contains a basis for the rational Krylov subspace $\mathcal{K}(A^*, C^*, \overline{\sigma}_k)$, then both the approximation X_k^{kry} of the Riccati solution obtained by the rational Krylov subspace method and the approximation X_k^{adi} obtained by a Riccati ADI iteration satisfy

$$X_k^{\text{kry}} = U_k Y_k^{\text{kry}} U_k^*, \quad X_k^{\text{adi}} = U_k Y_k^{\text{adi}} U_k^*,$$

for some matrices $Y_k^{\text{kry}}, Y_k^{\text{adi}} \in \mathbb{C}^{pk \times pk}$. The columns of both X_k^{kry} and X_k^{adi} belong to the same subspace, and the only difference between the methods is the choice of the linear combination of columns of U_k , i.e. the choice of the small matrix Y_k . The rational Krylov subspace method [35] generates its Y_k^{kry} by solving the projected Riccati equation, while the Riccati ADI methods do it via direct formulas such as the one in (12).

4 Shift selection in the RADI algorithm

The problem of choosing the shifts in order to accelerate the convergence of the Riccati ADI iteration is very similar to the one for the Lyapunov ADI method. Thus we apply and discuss the techniques presented in [31, 29, 6, 2] in the context of the Riccati equation, and compare them in several numerical experiments.

Penzl shifts. We first note that, by using the formula $R_k^{(1)}$ of Lemma 1 and by telescoping the recursive definition of V_k , we have $\mathcal{R}(X_k) = R_k^{(1)}(R_k^{(1)})^*$, where

$$R_k^{(1)} = (A^* - X_k G - \overline{\sigma}_k I) \left(\prod_{j=2}^k (A^* - X_{j-1} G + \sigma_j I)^{-1} (A^* - X_{j-1} G - \overline{\sigma}_{j-1} I) \right) \times \\ \times (A^* + \sigma_1 I)^{-1} C^*$$

In case of the Lyapunov equation (when $G = 0$), taking norms leads to the familiar expression [24, 31, 37]

$$\|\mathcal{R}(X_k)\| \leq \kappa(A)^2 \|C\|^2 \cdot \max_{i=1, \dots, n} \prod_{j=1}^k \frac{|\lambda_i^A - \sigma_j|^2}{|\lambda_i^A + \overline{\sigma}_j|^2}, \quad (27)$$

where $\kappa(A)$ is the condition number of the eigenvector matrix in the eigenvalue decomposition of A , and λ_i^A are the eigenvalues of A . When $G \neq 0$, it is more difficult to obtain an expression such as (27), since the eigenvector matrix cannot be factored out and canceled between the products of the shifted closed loop matrices.

Nevertheless, Simoncini and Lin [25] have shown that the convergence of the Riccati ADI iteration is related to the expression

$$\max_{i=1, \dots, n} \prod_{j=1}^k \frac{|\lambda_i^{\mathcal{H}} - \sigma_j|}{|\lambda_i^{\mathcal{H}} + \overline{\sigma}_j|}$$

being small, where $\lambda_i^{\mathcal{H}}$ are now the stable eigenvalues of $\mathcal{H}$. Thus it is reasonable to use Penzl shifts [29] for the RADI iteration as well. However, these shifts should be generated by using Krylov subspaces of the Hamiltonian matrix $\mathcal{H}$ instead of A —that is, the shifts are chosen among the Ritz values of $\mathcal{H}$, in order to approximate the eigenvalues of $\mathcal{H}$. Note that due to the low rank of Q and G we can expect that most of the eigenvalues of A are close to the eigenvalues of $\mathcal{H}$, see the discussion in [2]. Thus in many cases the Penzl shifts generated by A should suffice as well.

Residual Hamiltonian shifts. Penzl shifts require significant preprocessing computation: in order to approximate the eigenvalues of $M = A$ or $M = \mathcal{H}$, one has to build Krylov subspaces with matrices M and M^{-1} . All the shifts are computed in this preprocessing stage, and then simply cycled during the (R)ADI iteration.

An alternative approach is to generate each shift just before it is used. This way we hope to compute a shift which will better adapt to the current stage of the algorithm. One such approach is motivated by Theorem 1 and the discussion about shift selection in [2]. The Hamiltonian matrix

$$\tilde{\mathcal{H}} = \begin{bmatrix} \tilde{A} & G \\ \tilde{C}^* \tilde{C} & -\tilde{A}^* \end{bmatrix}$$

is associated to the residual equation (10), where $\Xi = X_k$ is the approximation after k steps of the RADI iteration. If $(\lambda, [\begin{smallmatrix} r \\ q \end{smallmatrix}])$ is a stable eigenpair of $\tilde{\mathcal{H}}$, and $\sigma_{k+1} = \lambda$ is used as the shift, then

$$X_k \leq X_{k+1} = X_k - q(q^* r)^{-1} q^* \leq X.$$

In order to converge as fast as possible to X , it is better to choose such eigenvalue λ for which the update is largest, i.e. the one that maximizes $\|q(q^* r)^{-1} q^*\|$. Note that as the RADI iteration progresses and the residual matrix $\mathcal{R}(\Xi) = \tilde{C}^* \tilde{C}$ converges to zero, the structure of eigenvectors of $\tilde{\mathcal{H}}$ that belong to its stable eigenvalues is such that $\|q\|$ becomes smaller and smaller. Thus one can further simplify the shift optimality condition, and use the eigenvalue λ such that the corresponding q has the largest norm—this is also in line with the discussion in [2].

However, in practice it is computationally very expensive to determine such an eigenvalue, since the matrix $\tilde{\mathcal{H}}$ is of order $2n$. We can approximate its eigenpairs through projection onto some subspace. If U is an orthonormal basis of the chosen subspace, then

$$(U^* \tilde{A} U)^* \tilde{X}^{\text{proj}} + \tilde{X}^{\text{proj}} (U^* \tilde{A} U) + (U^* \tilde{C}^*) (U^* \tilde{C}^*)^* - \tilde{X}^{\text{proj}} (U^* B) (U^* B)^* \tilde{X}^{\text{proj}} = 0$$

is the projected residual Riccati equation with the associated Hamiltonian matrix

$$\tilde{\mathcal{H}}^{\text{proj}} = \begin{bmatrix} U^* \tilde{A} U & (U^* B) (U^* B)^* \\ (U^* \tilde{C}^*) (U^* \tilde{C}^*)^* & -(U^* \tilde{A} U)^* \end{bmatrix}. \quad (28)$$

Approximate eigenpairs of $\tilde{\mathcal{H}}$ are $(\hat{\lambda}, [\begin{smallmatrix} \hat{r} \\ \hat{q} \end{smallmatrix}])$, where $(\hat{\lambda}, [\begin{smallmatrix} \hat{r} \\ \hat{q} \end{smallmatrix}])$ are eigenpairs of $\tilde{\mathcal{H}}^{\text{proj}}$. Thus a reasonable choice for the next shift is such $\hat{\lambda}$, for which $\|U \hat{q}\| = \|\hat{q}\|$ is the largest.

We still have to define the subspace $\text{span}\{U\}$. One option is to use V_k (or, equivalently, the last p columns of the matrix Z_k), which works very well in practice unless $p = 1$. When $p = 1$, all the generated shifts are real, which can make the convergence slow in some cases. Then it is better to choose the last ℓ columns of the matrix Z_k ; usually already $\ell = 2$ or $\ell = 5$ or a small multiple of p will suffice. We point out that this shift selection strategy has been adapted to low-rank Newton-ADI type methods for symmetric and non-symmetric Riccati equations in [18, 7]. An ultimate option is to use the entire Z_k , which we denote as $\ell = \infty$. This is obviously more computationally demanding, but it provides fast convergence in all cases we tested.

Residual minimizing shifts. The two successive residual factors are connected via the formula

$$R_{k+1} = (A^* - X_{k+1} G - \overline{\sigma_{k+1}} I) (A^* - X_k G + \sigma_{k+1} I)^{-1} R_k.$$


Our goal is to choose the shifts so that the residual drops to zero as quickly as possible. Locally, once X_k is computed, this goal is achieved by choosing $\sigma_{k+1} \in \mathbb{C}_-$ so that $\|R_{k+1}\|$ is minimized. This concept was intrinsically proposed in [6] for the low-rank Lyapunov and Sylvester ADI methods. In complete analogy, we define a rational function f in the variable σ by

$$f(\sigma) := \|(A^* - X_{k+1}(\sigma) G - \bar{\sigma} I) (A^* - X_k G + \sigma I)^{-1} R_k\|^2, \quad (29)$$

and wish to find

$$\operatorname{argmin}_{\sigma \in \mathbb{C}_-} f(\sigma);$$

note that $X_{k+1}(\sigma) = X_k + V_{k+1}(\sigma) \tilde{Y}_{k+1}^{-1}(\sigma) V_{k+1}^*(\sigma)$ is also a function of σ . Since f involves large matrices, we once again project the entire equation to a chosen subspace U , and solve the optimization problem defined by the matrices of the projected problem. The optimization problem is



(a) Ratios $\rho^{\text{proj}}(\sigma) = \|R_{14}^{\text{proj}}(\sigma)\|/\|R_{13}^{\text{proj}}\|$ for the projected equation of dimension 13.

(b) Ratios $\rho(\sigma) = \|R_{14}(\sigma)\|/\|R_{13}\|$ for the original equation of dimension 10648.

Figure 1: Each point σ of the complex plane is colored according to residual reduction obtained when σ is taken as the shift in the 14th iteration of RADI.

solved numerically. Efficient optimization solvers use the gradient of the function f ; after a laborious computation one can obtain an explicit formula for the case $p = 1$:

$$\nabla f(\sigma_R, \sigma_I) = \begin{bmatrix} 2 \operatorname{Re} \left(R_{k+1}^* \cdot \left(\left(\frac{1}{\sigma_R} I - \tilde{A}^{-1} - \frac{1}{2\sigma_R} (X_{k+1} G \tilde{A}^{-1} + X_{k+1} \tilde{A}^{-*} G) \right) \Delta \right) \right) \\ -2 \operatorname{Im} \left(R_{k+1}^* \cdot \left(\left(-\tilde{A}^{-1} - \frac{1}{2\sigma_R} (X_{k+1} G \tilde{A}^{-1} - X_{k+1} \tilde{A}^{-*} G) \right) \Delta \right) \right) \end{bmatrix}.$$

Here $\sigma = \sigma_R + i\sigma_I$, $\tilde{A} = A^* - X_k G - \sigma I$, $X_{k+1} = X_{k+1}(\sigma)$, $R_{k+1} = R_{k+1}(\sigma)$, and $\Delta = R_{k+1}(\sigma) - R_k$.

For $p > 1$, a similar formula can be derived, but one should note that the function f is not necessarily differentiable at every point σ , see, e.g., [28]. Thus, a numerically more reliable heuristic is to artificially reduce the problem once again to the case $p = 1$. This can be done in the following way: let v denote the right singular vector corresponding to the largest singular value of the matrix R_k . Then $R_k \in \mathbb{C}^{n \times p}$ in (29) is replaced by the vector $R_k v \in \mathbb{C}^n$.

Since numerical optimization algorithms usually require a starting point for the optimization, the two shift generating approaches may be combined: the residual Hamiltonian shift can be used as the starting point in the optimization for the second approach. However, from our numerical experience we conclude that the additional computational effort invested in the post-optimization of the residual Hamiltonian shifts often does not contribute to the convergence. The rationale is given in the following example.

Example 1. Consider the Riccati equation given in Example 5.2 of [33]: the matrix A is obtained by the centered finite difference discretization of the differential equation

$$\partial_t x = \Delta x - 10x \partial_x x - 1000y \partial_y x - 10 \partial_z x + b(x, y)u(t),$$

on a unit cube with 22 nodes in each direction. Thus A is of order $n = 10648$; the matrices $B = C^* \in \mathbb{R}^{n \times p}$ are generated at random; let $p = 1$.

Suppose that 13 RADI iterations have already been computed, and that we need to compute a shift to be used in the 14th iteration. Let the matrix U contain an orthonormal basis for Z_{13} .

Figure 1a shows a region of the complex plane; stars are at locations of the stable eigenvalues of the projected Hamiltonian matrix (28). The one eigenvalue chosen as the residual Hamiltonian shift σ_{ham} is shown as 'x'. The residual minimizing shift σ_{opt} is shown as 'o'. Each point σ of the complex

plane is colored according to the ratio $\rho^{\text{proj}}(\sigma) = \|R_{14}^{\text{proj}}(\sigma)\|/\|R_{13}^{\text{proj}}\|$, where R^{proj} is the residual for the projected Riccati equation. The ratio $\rho^{\text{proj}}(\sigma_{\text{ham}}) \approx 0.54297$ is not far from the optimal ratio $\rho^{\text{proj}}(\sigma_{\text{opt}}) \approx 0.53926$.

On the other hand, Figure 1b shows the complex plane colored according to ratios for the original system of order 10648, $\rho(\sigma) = \|R_{14}(\sigma)\|/\|R_{13}\|$. Neither of the values $\rho(\sigma_{\text{ham}}) \approx 0.71510$ and $\rho(\sigma_{\text{opt}}) \approx 0.71981$ is optimal, but they both offer a reasonable reduction of the residual norm in the next step. In this case, σ_{ham} turns out even to give a slightly better residual reduction for the original equation than σ_{opt} , making the extra effort in running the numerical optimization algorithm futile.

5 Numerical experiments

In this section we show a number of numerical examples, with several objectives in mind. First, our goal is to compare different low-rank implementations of the Riccati ADI algorithm mentioned in this paper: the low-rank qADI proposed in [40, 41], the Cayley transformed subspace iteration [25, 26], and the complex and real variants of the RADI iteration (12). Second, we compare performance of the RADI approach against other methods for solving large-scale Riccati equations, namely the rational Krylov subspace method (RKSM) [35], the extended block Arnoldi (EBA) method [33, 19], and the Newton-ADI algorithm [8, 11, 18].

Finally, we discuss various shift strategies for the RADI iteration described in the previous section.

The numerical experiments are run on a desktop computer with a four-core Intel Core i5-4690K processor and 16GB RAM. All algorithms and testing routines are implemented and executed in MATLAB R2014a, running on Microsoft Windows 8.1.

Example 2. Consider again the Riccati benchmark *CUBE* from Example 1. We discuss two cases: $p = 1$ and $p = 10$.

The following table collects timings in seconds for four different low-rank implementations of the Riccati ADI algorithm. The table shows only the time needed to run 80 ADI iterations; time spent for computation of the shifts used by all four variants is not included (in this case, 20 precomputed Penzl shifts were used). All four variants compute exactly the same iterates, as we have proved in Theorem 2.

Implementation	time, $p = 1$	time, $p = 10$
Wong and Balakrishnan [40, 41]	127.61	750.89
Cayley subspace iteration [25, 26]	21.67	167.02
RADI – Algorithm 1	21.51	51.92
RADI – Algorithm 2	11.14	26.35

Clearly, the real variant of iteration (12), implemented as in Algorithm 2, outperforms all the others.¹ Thus we use this implementation in the remaining numerical experiments. The RADI algorithms mostly obtain the advantage over the Cayley subspace iteration by not having to perform any orthogonalization, which the latter algorithm needs in order to compute the residuals. This advantage is more emphasized for larger values of p . Also, the times for the algorithm of Wong and Balakrishnan shown in the table do not include the (very costly) computation of the residuals at all, so their actual execution times are even higher.

Next, we compare various shift strategies for RADI, as well as EBA, RKSM, and Newton-ADI algorithms. For RADI, we have the following strategies:

- 20 precomputed Penzl shifts (“RADI – Penzl”) generated by using the Krylov subspaces of dimensions 40 with matrices A and A^{-1} ;
- residual Hamiltonian shifts (“RADI – Ham”), with $\ell = 2p$, $\ell = 6p$, and $\ell = \infty$;
- residual minimizing shifts (“RADI – Ham+Opt”), with $\ell = 2p$, $\ell = 6p$, and $\ell = \infty$.

¹Note that the generated Penzl shifts come in complex conjugate pairs.

For the RKSM, we have implemented the algorithm so that the use of complex arithmetic is minimized by merging two consecutive steps with complex conjugate shifts. The RKSM shift strategies include:

- Penzl shifts, computed in the same way as for the RADI iteration;
- adaptive shift strategy, implemented as described in [16].

For all methods, the threshold for declaring convergence is reached once the relative residual is less than $\text{tol} = 10^{-11}$. A summary of the results for all the different methods and strategies is shown in Table 1. The column “final subspace dimension” displays the number of columns of the matrix Z , where $X \approx ZZ^*$ is the final computed approximation. Dividing this number by p (for EBA, by $2p$), we obtain the number of iterations used in a particular method. Just for the sake of completeness, we have also included a variant of the Newton-ADI algorithm [8] with Galerkin projection [11]. Without the Galerkin projection, the Newton-ADI algorithm could not compete with the other methods. The recent developments from [18], which make the Newton-ADI algorithm more competitive, are beyond the scope of this study.

Convergence history for CUBE is plotted in Figure 2; to reduce the clutter, only the selected few methods are shown.

It is interesting to analyze the timing breakdown for RADI and RKSM methods, especially for $p = 10$ where a significant amount of time is spent for tasks other than solving linear systems.

method	subtask	time, $p = 10$
RADI – Penzl: 135 iterations	precompute shifts	5.31
	solve linear systems	43.24
	total	49.19
RADI – Ham, $\ell = 2p$: 139 iterations	solve linear systems	46.42
	compute shifts dynamically	1.76
	total	48.79
RADI – Ham, $\ell = 6p$: 100 iterations	solve linear systems	32.73
	compute shifts dynamically	2.75
	total	35.92
RADI – Ham, $\ell = \infty$: 74 iterations	solve linear systems	24.74
	compute shifts dynamically	32.44
	total	57.51
RKSM – adaptive: 77 iterations	solve linear systems	17.87
	orthogonalization	4.00
	compute shifts dynamically	11.16
	solve projected equations	39.52
	total	76.54

As ℓ increases, the cost of computing shifts increases as well—the projection subspace gets larger, and more effort is needed to orthogonalize its basis and compute the eigenvalue decomposition of the projected Hamiltonian matrix. This effort is, in this case, awarded by a decrease in the number of iterations. However, there is a trade-off here: the extra computation does outweigh the saving in the number of iterations for sufficiently large ℓ .


Example 3. Next, we run the Riccati solvers for the well-known benchmark examples *CHIP* and *FLOW*. All coefficient matrices for the Riccati equation are taken as they are found in the Oberwolfach Model Reduction Benchmark Collection [20]. Here we solve the generalized Riccati equation (14).

The cost of precomputing shifts is very high in case of *CHIP*. One fact not shown in the table is that all algorithms which compute shifts dynamically have already solved the Riccati equation before those using precomputed shifts have even started.


FLOW shows the benefit of efficient dynamical shift computation. While all methods (apart from “RADI – Penzl”) need approximately the same number of iterations, those that can compute shifts quickly (“RADI – Ham, $\ell = 2p, 6p$ ” and “RADI – Ham+Opt, $\ell = 2p$ ”) are the fastest. On the other

example	method	no. iterations	final subspace dim.	time
CUBE $n = 10648, m = 1, p = 1$	RADI – Penzl	97	97	18.96
	RADI – Ham, $\ell = 2p$	119	119	17.10
	RADI – Ham, $\ell = 6p$	99	99	14.15
	RADI – Ham, $\ell = \infty$	75	75	11.60
	RADI – Ham+Opt, $\ell = 2p$	122	122	17.87
	RADI – Ham+Opt, $\ell = 6p$	103	103	16.70
	RADI – Ham+Opt, $\ell = \infty$	108	108	18.44
	RKSM – Penzl	78	78	17.50
	RKSM – adaptive	83	83	15.33
	EBA	110	220	26.13
	Newton-ADI	2 outer, 296 inner	192	42.11
CUBE $n = 10648, m = 10, p = 10$	RADI – Penzl	135	1350	49.19
	RADI – Ham, $\ell = 2p$	139	1390	48.79
	RADI – Ham, $\ell = 6p$	100	1000	35.92
	RADI – Ham, $\ell = \infty$	74	740	57.51
	RADI – Ham+Opt, $\ell = 2p$	87	870	30.59
	RADI – Ham+Opt, $\ell = 6p$	90	900	33.20
	RADI – Ham+Opt, $\ell = \infty$	90	900	119.55
	RKSM – Penzl	80	800	80.01
	RKSM – adaptive	77	770	76.54
	EBA	90	1800	1628.75
	Newton-ADI	2 outer, 202 inner	1960	75.60
FLOW $n = 9669, m = 1, p = 5$	RADI – Penzl	106	530	8.25
	RADI – Ham, $\ell = 2p$	59	295	3.95
	RADI – Ham, $\ell = 6p$	61	305	4.54
	RADI – Ham, $\ell = \infty$	59	295	7.50
	RADI – Ham+Opt, $\ell = 2p$	51	255	4.09
	RADI – Ham+Opt, $\ell = 6p$		did not converge	
	RADI – Ham+Opt, $\ell = \infty$		did not converge	
	RKSM – Penzl	58	290	10.55
	RKSM – adaptive	52	260	8.06
	EBA	51	510	26.36
	Newton-ADI	2 outer, 155 inner	480	10.16
CHIP $n = 20082, m = 1, p = 5$	RADI – Penzl	33	165	51.57
	RADI – Ham, $\ell = 2p$	36	180	30.32
	RADI – Ham, $\ell = 6p$	29	145	24.36
	RADI – Ham, $\ell = \infty$	26	130	22.64
	RADI – Ham+Opt, $\ell = 2p$	29	145	23.97
	RADI – Ham+Opt, $\ell = 6p$	26	130	22.26
	RADI – Ham+Opt, $\ell = \infty$	25	125	22.33
	RKSM – Penzl	24	120	44.79
	RKSM – adaptive	25	125	23.50
	EBA	25	250	28.15
	Newton-ADI	2 outer, 64 inner	204	54.04
IFISS $n = 66049, m = 5, p = 5$	RADI – Penzl	> 50	> 250	
	RADI – Ham, $\ell = 2p$	21	110	17.21
	RADI – Ham, $\ell = 6p$	19	95	15.37
	RADI – Ham, $\ell = \infty$	20	100	17.46
	RADI – Ham+Opt, $\ell = 2p$	27	135	21.12
	RADI – Ham+Opt, $\ell = 6p$		did not converge	
	RADI – Ham+Opt, $\ell = \infty$		did not converge	
	RKSM – Penzl	34	170	54.49
	RKSM – adaptive	26	130	22.28
	EBA	11	110	18.30
	Newton-ADI	2 outer, 46 inner	250	38.05

Table 1: Results of the numerical experiments.



(a) Relative residual versus the subspace dimension used by an algorithm.



(b) Relative residual versus time.


Figure 2: Algorithm performances for benchmark CUBE ($n = 10648, m = 1, p = 10$)

hand, the version with residual minimizing shifts does not converge for $\ell = 6p, \infty$: it quickly reaches the relative residual of about 10^{-10} , and then gets stuck by continually using shifts very close to zero. We have not observed such behavior with residual Hamiltonian shifts.

Example 4. For the final example, we use the *IFISS 3.2* finite-element package [32] to generate the coefficient matrices for a generalized Riccati equation. We choose the provided example *T-CD 2* which represents a finite element discretization of a two-dimensional convection diffusion equation on a square domain. The leading dimension is $n = 66049$, with E symmetric positive definite, and A non-symmetric. The matrix B consists of $m = 5$ randomly generated columns, and $C = [C_1, 0]$ with random $C_1 \in \mathbb{R}^{5 \times 5}$ ($p = 5$).

In this example, the RADI iteration with Penzl shifts converges very slowly. The RADI iteration with dynamically generated shifts are the fastest among all methods, and manage to converge in the smallest number of steps. Similarly as in *FLOW*, there is a problem with residual minimizing shifts with $\ell = 6p, \infty$, which are able to reach relative residual of about 10^{-7} , and then stagnate.

Let us summarize the findings from these and a number of other numerical examples we used to test the algorithms. The RADI algorithm using Penzl shifts tends to perform worse than the RKSM using the same shifts, and in general needs most iterations of all the variants listed above. On the other hand, using dynamically generated shifts for the RADI iteration has many benefits: the number of iterations is reduced, and is typically comparable to the RKSM. Furthermore, the total amount of time needed to run a fixed number of RADI iteration steps is far lower when the shifts are not precomputed—the accumulated time to generate shifts dynamically is lower than the time needed to build Krylov subspaces for the Penzl shifts. Also, there frequently exists a small value of ℓ for which one or both of the dynamical shift strategies converge in a number of iterations that is comparable to, or even outperform RKSM. Since the computation of shifts for the RADI iteration is close to negligible in such cases, and each iteration of the main algorithm is very efficient compared to RKSM (no orthogonalization; residual for free), the RADI algorithm may outperform both variants of RKSM. However, an a-priori method of determining a sufficiently small ℓ with such properties is still to be found, and a topic of our future research. Note that $\ell = \infty$ in all cases is a good choice; it is not always the fastest among the varying dynamic shift strategies, but consistently outperforms RKSM.



(a) Relative residual versus the subspace dimension used by an algorithm.

(b) Relative residual versus time.

Figure 3: Algorithm performances for benchmark IFISS ($n = 66049, m = 5, p = 5$)

6 Conclusion

In this paper, we have presented a new low-rank RADI algorithm for computing solutions of large scale Riccati equations. We have shown that this algorithm produces exactly the same iterates as three previously known methods (for which we suggest the common name “Riccati ADI methods”), but it does so in a computationally far more efficient way. As with other Riccati solvers, the performance is heavily dependent on the choice of shift parameters. We have suggested several strategies on how this may be done; some of them show very promising results, making the RADI algorithm competitive with the fastest large scale Riccati solvers.

7 Acknowledgements

Part of this work was done while the second author was a postdoctoral researcher at Max Planck Institute Magdeburg, Germany. The second author would also like to acknowledge the support of the Croatian Science Foundation under grant HRZZ-9345.

References

- [1] L. Amodei and J.-M. Buchot. An invariant subspace method for large-scale algebraic Riccati equation. *Appl. Numer. Math.*, 60(11):1067–1082, 2010.
- [2] P. Benner and Z. Bujanović. On the solution of large-scale algebraic Riccati equations by using low-dimensional invariant subspaces. *Linear Algebra and Its Applications*, (488):430–459, 2016.
- [3] P. Benner, P. Kürschner, and J. Saak. A Reformulated Low-Rank ADI Iteration with Explicit Residual Factors. *Proc. Appl. Math. Mech.*, 13(1):585–586, 2013.
- [4] P. Benner, P. Kürschner, and J. Saak. An Improved Numerical Method for Balanced Truncation for Symmetric Second Order Systems. *Math. Comput. Model. Dyn. Sys.*, 19(6):593–615, 2013.
- [5] P. Benner, P. Kürschner, and J. Saak. Efficient handling of complex shift parameters in the low-rank Cholesky factor ADI method. *Numerical Algorithms*, 62(2):225–251, 2013.

- [6] P. Benner, P. Kürschner, and J. Saak. Self-Generating and Efficient Shift Parameters in ADI Methods for Large Lyapunov and Sylvester Equations. *Electr. Trans. Num. Anal.*, 43:142–162, 2014.
- [7] P. Benner, P. Kürschner, and J. Saak. Low-Rank Newton-ADI methods for Large Nonsymmetric Algebraic Riccati Equations. *J. Frankl. Inst.*, 2015. Accepted; Preprint available from <http://www.mpi-magdeburg.mpg.de/preprints/>.
- [8] P. Benner, J.-R. Li, and T. Penzl. Numerical Solution of Large Lyapunov equations, Riccati Equations, and Linear-Quadratic Control Problems. *Numer. Lin. Alg. Appl.*, 15(9):755–777, 2008.
- [9] P. Benner, R.-C. Li, and N. Truhar. On the ADI Method for Sylvester Equations. *J. Comput. Appl. Math.*, 233(4):1035–1045, december 2009.
- [10] P. Benner and J. Saak. Efficient solution of large scale Lyapunov and Riccati equations arising in model order reduction problems. *Proc. Appl. Math. Mech.*, 8(1):10085–10088, 2008.
- [11] P. Benner and J. Saak. A Galerkin-Newton-ADI Method for Solving Large-Scale Algebraic Riccati Equations. Preprint SPP1253-090, SPP1253, January 2010. <http://www.am.uni-erlangen.de/home/spp1253/wiki/index.php/Preprints>.
- [12] P. Benner and J. Saak. Numerical solution of large and sparse continuous time algebraic matrix Riccati and Lyapunov equations: a state of the art survey. *GAMM Mitteilungen*, 36(1):32–52, August 2013.
- [13] Peter Benner. Theory and Numerical Solution of Differential and Algebraic Riccati Equations. In Peter Benner, Matthias Bollhöfer, Daniel Kressner, Christian Mehl, and Tatjana Stykel, editors, *Numerical Algebra, Matrix Theory, Differential-Algebraic Equations and Control Theory*, pages 67–105. Springer International Publishing.
- [14] D. Bini, B. Iannazzo, and B. Meini. *Numerical Solution of Algebraic Riccati Equations*. Fundamentals of Algorithms. SIAM, 2012.
- [15] E. K.-W. Chu, H.-Y. Fan, and W.-W. Lin. A structure-preserving doubling algorithm for continuous-time algebraic Riccati equations. *Linear Algebra Appl.*, 396:55–80, 2005.
- [16] V. Druskin and V. Simoncini. Adaptive rational Krylov subspaces for large-scale dynamical systems. *Systems and Control Letters*, 60(8):546–560, 2011.
- [17] G. H. Golub and C. F. Van Loan. *Matrix Computations*. Johns Hopkins University Press, Baltimore, fourth edition, 2013.
- [18] M. Heinkenschloss, H. K. Weichelt, P. Benner, and J. Saak. Inexact low-rank Newton-ADI method for large-scale algebraic Riccati equations. Technical Report MPIMD/15-06, Max Planck Institute Magdeburg Preprints, 2015. Available from <http://www.mpi-magdeburg.mpg.de/preprints/>.
- [19] M. Heyouni and K. Jbilou. An extended block Arnoldi algorithm for large-scale solutions of the continuous-time algebraic Riccati equation. *Electr. Trans. Num. Anal.*, 33:53–62, 2009.
- [20] J. G. Korvink and E. B. Rudnyi. Oberwolfach Benchmark Collection. In P. Benner, D. C. Sorensen, and V. Mehrmann, editors, *Dimension Reduction of Large-Scale Systems*, volume 45 of *Lecture Notes in Computational Science and Engineering*, pages 311–315. Springer Berlin Heidelberg, 2005.
- [21] P. Lancaster and L. Rodman. *The Algebraic Riccati Equation*. Oxford University Press, Oxford, 1995.

- [22] A. J. Laub. A Schur Method for Solving Algebraic Riccati Equations. *IEEE Trans. Automat. Control*, AC-24:913–921, 1979.
- [23] N. Levenberg and L. Reichel. A generalized ADI iterative method. *Numer. Math.*, 66(1):215–233, 1993.
- [24] J.-R. Li and J. White. Low Rank Solution of Lyapunov Equations. *SIAM J. Matrix Anal. Appl.*, 24(1):260–280, 2002.
- [25] Y. Lin and V. Simoncini. A new subspace iteration method for the algebraic Riccati equation. *Numerical Linear Algebra with Applications*, 22(1):26–47, 2015.
- [26] A. Massoudi, M. R. Opmeer, and T. Reis. The ADI method for algebraic Riccati equations. Technical report, Hamburger Beiträge zur Angewandten Mathematik 2014-16, Hamburg, 2014.
- [27] V. Mehrmann and E. Tan. Defect Correction Methods for the Solution of Algebraic Riccati Equations. *IEEE Trans. Automat. Control*, 33:695–698, 1988.
- [28] Michael L. Overton. Large-Scale Optimization of Eigenvalues. *SIAM J. Optimiz.*, 2(1):88–120, 1992.
- [29] T. Penzl. LYAPACK Users Guide. Technical Report SFB393/00-33, Sonderforschungsbereich 393 *Numerische Simulation auf massiv parallelen Rechnern*, TU Chemnitz, 09107 Chemnitz, Germany, 2000. Available from <http://www.tu-chemnitz.de/sfb393/sfb00pr.html>.
- [30] J. Saak. *Efficient Numerical Solution of Large Scale Algebraic Matrix Equations in PDE Control and Model Order Reduction*. PhD thesis, TU Chemnitz, July 2009. Available from <http://nbn-resolving.de/urn:nbn:de:bsz:ch1-200901642>.
- [31] J. Sabino. *Solution of Large-Scale Lyapunov Equations via the Block Modified Smith Method*. PhD thesis, Rice University, Houston, Texas, June 2007. Available from: http://www.caam.rice.edu/tech_reports/2006/TR06-08.pdf.
- [32] D. Silvester, H. Elman, and A. Ramage. Incompressible Flow and Iterative Solver Software (IFISS) version 3.2, May 2012.
- [33] V. Simoncini. A New Iterative Method for Solving Large-Scale Lyapunov Matrix Equations. *SIAM Journal on Scientific Computing*, 29(3):1268–1288, 2007.
- [34] V. Simoncini. Computational methods for linear matrix equations. Available at <http://www.dm.unibo.it/~simoncin/>, March 2013.
- [35] V. Simoncini, D. Szyld, and M. Monsalve. On two numerical methods for the solution of large-scale algebraic Riccati equations. *IMA J. Numer. Anal.*, 34(3):904–920, 2014.
- [36] E. Wachspress. ADI Iteration Parameters for the Sylvester Equation, 2000. Available from the author.
- [37] E. Wachspress. *The ADI Model Problem*. Springer New York, 2013.
- [38] E.L. Wachspress. Iterative solution of the Lyapunov matrix equation. *Appl. Math. Letters*, 107:87–90, 1988.
- [39] T. Wolf and H. K.-F. Panzer. The ADI iteration for Lyapunov equations implicitly performs H2 pseudo-optimal model order reduction. Technical Report 1309.3985, ArXiv e-prints, 2013.
- [40] N. Wong and V. Balakrishnan. Quadratic Alternating Direction Implicit Iteration for the Fast Solution of Algebraic Riccati Equations. In *Proc. Int. Symposium on Intelligent Signal Processing and Communication Systems*, pages 373–376, 2005.
- [41] Ngai Wong and V. Balakrishnan. Fast Positive-Real Balanced Truncation Via Quadratic Alternating Direction Implicit Iteration. *IEEE Trans. Comput.-Aided Design Integr. Circuits Syst.*, 26(9):1725–1731, September 2007.